



# MK101 MOBILE SERIES

## LIGHTWEIGHT PADDED HEADSET FOR MOBILE RADIOS

### ABOUT THE MK101 MOBILE SERIES

This MK101 mobile headset combines superior comfort with professional-grade performance. Designed to be lightweight, this headset includes a padded headband to provide all-day wearability, while the noise-reducing boom microphone ensures clear communication in any type of environment. Built with a rugged over-the-head design, this product is ideal for users who require reliable comfort during extended use.



### FEATURES

- Lightweight over-the-head headset
- Padded, adjustable metal headband w/ replaceable padding
- Adjustable padded T-Bar
- Adjustable speaker housing assembly
- Replaceable leather style speaker cushion
- Flexible metal boom microphone with replaceable windsock
- Reinforced strain reliefs at all attachment points
- Noise reducing condenser microphone element
- Rugged in-line PTT switch
- Flexible metal boom rotates for use on either ear



**OPTIONAL PTT-FSI FOOT SWITCH WITH 3.5MM PLUG**



### MOBILE RADIO DIRECT - HARDWIRED HEADSET KITS



PART #	DESCRIPTION	FOOT SWITCH OPTION
<b>MK101-MM2</b>	Headset Kit for Motorola CDM/16-Pin Mobiles (Rear Plug-In Connector)	<b>YES</b>
<b>MK101-MM3</b>	Headset Kit for Motorola XPR/TRBO Mobiles (Rear Plug-In Connector)	<b>NO</b>
<b>MK101-MM6</b>	Headset Kit for Motorola XTL500/ATX4500 Mobiles (Rear Plug-In Connector)	<b>YES</b>
<b>MK101-KM1</b>	Headset Kit for Kenwood TK* Mobiles (RJ45/3.5MM Connector)	<b>YES</b>
<b>MK101-CM1</b>	Headset Kit for Icom IC-F* Mobiles (RJ45/3.5MM Connector)	<b>YES</b>
<b>MK101-VM1</b>	Headset Kit for Vertex EXV* & VX* Mobiles (RJ45/3.5MM Connector)	<b>YES</b>
<b>MK101-FPTT</b>	Foot Pedal PTT with Straight Cord, 3.5mm Plug (for MK101 Mobile Kit with 3.5mm Jack Foot PTT Option)	-

Replacement headset covers, earpads, headbands, and windscreens available – Please contact us for more information.

**(\*) This kit is compatible with a wide range of models. For a list of supported devices, please refer to our website or contact our team directly for further assistance.**

### QUESTIONS?

Contact us today to learn more about your team's communication needs.

For any questions or inquiries, please call CanCom at (705) 326-5677 or send us an email us to [info@cancomsales.com](mailto:info@cancomsales.com), and one of our team members will be happy to assist.

### PRODUCT SPECIFICATIONS

MICROPHONE	
TYPE	Noise Canceling Condenser Mic
SPEAKER	
SIZE	40mm Outer Diameter
IMPEDENCE	300Ω at 1kHz
POWER RATING	Nominal 10mW RMS, 20mW Max.
OUTPUT SOUND PRESSURE LEVEL	96 ± 3dB / 100mW / 1cm
FREQUENCY RANGE	100hz ~ 10kHz
DISTORTION	5% Max. at 1kHz / 100mW